

# Digital Cycle Counter

Submittal  
Data Sheet



## Applications

The Digital Cycle Counter is an event monitor that records the number of times the input contact switches. Suitable for use with any dry contact signal. Outdoor-rated; raintight enclosure with viewing window. Battery-powered (long-life lithium battery included). Input sensor not included.



## General

Oreco's Digital Cycle Counter is a battery-powered digital counter in a clear, raintight electrical enclosure. The counter registers one count whenever an input contact closes. The watertight enclosure can be installed indoors or outdoors. Any input sensor with a contact can be used.

## Standard Model

AMDDC

## Specifications

### Materials of Construction:

Battery:	Lithium; has a 7-year expected life
3/4" Conduit Fitting:	PVC
Counter:	Red Lion <sup>®</sup> CUB7 digital counter with LCD display. Operating voltage: 3V Display height: 0.35"
Electrical Enclosure:	Clear cover, watertight; measures 5" x 3" x 3". NEMA 4X rated